

power dissipation in W:



Main

| | |
|------------------------------------|--------------------------------------|
| Range of product | Harmony XVB Universal |
| Product or component type | Indicator bank |
| Beacon or indicator bank unit type | Illuminated unit |
| Signalling type | Flashing |
| Mounting diameter | 70 mm |
| Component name | XVBC |
| Material | Polycarbonate |
| Light source | Orange integral flash discharge tube |
| Bulb type | Flash discharge tube |
| [Us] rated supply voltage | 24 V AC/DC |
| Flash energy | 5 J |

Complementary

| | |
|--|---|
| Assembly style | Customer assembly, up to 5 units |
| Connections - terminals | Screw clamp terminals : <= 1 x 1.5 mm ² with cable end |
| [Ui] rated insulation voltage | 250 V conforming to IEC 60947-1 |
| Nominal voltage limit | 0.85...1.1 Un conforming to IEC 60947-5-1 |
| Current consumption | < 350 mA DC < 550 mA AC |
| [Uimp] rated impulse withstand voltage | 4 kV conforming to IEC 60947-1 |
| Flashing frequency | 1 Hz |
| Product weight | 0.295 kg |

Environment

| | |
|--|--|
| Product certifications | CCC CSA C22-2 No 14 GOST UL 508 |
| Standards | EN/IEC 60947-5-1 |
| Protective treatment | TC |
| Ambient air temperature for storage | -40...70 °C |
| Ambient air temperature for operation | -25...50 °C |
| Class of protection against electric shock | Class I on support tube conforming to IEC 61140 Class II on base unit conforming to IEC 61140 |
| IP degree of protection | IP65 on fixing base XVBZ0. conforming to IEC 60529 IP66 on base unit conforming to IEC 60529 |
| NEMA degree of protection | NEMA 4X indoor conforming to UL 508 |
| RoHS EUR conformity date | 0730 |
| RoHS EUR status | Compliant |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.